



# Certified Capability List

This Capability List is based on a certification session performed by the *TALQ Certification Tool (v2.6.1-online.7)* on 2024-10-27 11:34:04.889 +0100.

The Capability List is a consolidated list of TALQ features which are implemented in a product.

The tool has successfully performed 41 tests.

## Product details

**Product Name** TBC v2.6 - Lighting

**Company** Signify

**Type** GATEWAY

**Notes**

**Generated on** 2024-10-27 11:34:04.889 +0100

**Supported profiles** • Lighting

**API version certified:** 2.6.1

**Certification performed by app version:** 2.6.1-online.7

## Functional tests

The Functional Tests help customers understand the capabilities of a TALQ-certified product. All functional test cases are presented to provide comprehensive context, and successful completion of each test is indicated with a tick mark. Each Functional Test is related to a set of required TALQ technical test cases.

### Configuring

5 of 11

#### Support light point control features ✓

The Gateway successfully connects to a CMS and transmits its capabilities for light point control features and services.

CFG-1

#### Support cabinet control lighting features

The Gateway successfully connects to a CMS and transmits its capabilities for cabinet control lighting features and services.

CFG-2

#### Support sensor-based light point control features

The Gateway successfully connects to a CMS and transmits its capabilities for sensor-based light point control features and services.

CFG-3

**Discovery of the network of devices**



The Gateway transmits all its devices to the CMS together with their configuration and asset information.

**CFG-4**

**Initialize light point electrical alarm thresholds**



The Gateway is able to receive the light point electrical alarm thresholds from the CMS, including Lamp Voltage Too High/Low, Lamp Current Too High/Low, Active Power Too High/Low and Power Factor Too Low

**CFG-5**

**Initialize and change the cabinet control alarm thresholds**



The Gateway is able to receive the cabinet control electrical alarm thresholds from the CMS, including < to be defined >

**CFG-6**

**Initialize and change the light point parameters**

The Gateway is able to receive the light point parameters from the CMS.

**CFG-7**

**Initialize and change a group of luminaires**



The Gateway is able to handle a command from the CMS to set or change a group of light points to assign them a control program.

**CFG-8**

**Change the sampling frequency for measurements**

The Gateway is able to change the sampling of measurements and properly reflected in the next data log sent to the CMS.

**CFG-9**

**Change the reporting frequency for measurements**

The Gateway is able to change the reporting frequency (how often it sends data logs to the CSM) for measurements.

**CFG-10**

**Update the firmware of the hardware devices**

The Gateway supports data package service and accepts a data package to update firmware on a physical device.

**CFG-11**

**Monitoring**

**1 of 11**

**Measure and report basic electrical values (Current/Voltage/Active Power/Power Factor)**

The Gateways sends "valid values" for electrical values including mains voltage, current, active power and power factor to the CMS using one of the data logging service.

**MTG-1**

**Measure and report cumulating energy counter**

The Gateways sends "valid growing values" for energy counter to the CMS using one of the data logging service.

**MTG-2**

**Report lamps' number of operating hours**

The Gateways sends "valid growing values" for lamp operating hours counter to the CMS using one of the data logging service.

**MTG-3**

**Report lamps' number of switch-on counter**

The Gateways sends "valid growing values" for lamp switch-on counter to the CMS using one of the data logging service.

**MTG-4****Report lamps' number of supply loss counter**

The Gateways sends "valid growing values" for supply loss count to the CMS using one of the data logging service.

**MTG-5****Monitor the lamp level feedback when a manual override command is sent**

The Gateway receives a manual override command, sends it to the device and can report, using on-demand read as well as a data logger service, that the lamp level feedback is getting close to the command.

**MTG-6****Report temperature**

The Gateways sends temperature values to the CMS using one of the data logging service.

**MTG-8****Report presence detection**

The Gateways sends presence detection values to the CMS using one of the data logging service.

**MTG-9****Report noise level**

The Gateways sends noise level values to the CMS using one of the data logging service.

**MTG-10****Report light level**

The Gateways sends light level values to the CMS using one of the data logging service.

**MTG-11****Report firmware updating process**

The Gateway is able to report the firmware update events

**MTG-12****Controlling****2 of 7****Manual control over a light point**

The Gateway properly receives and handles a manual override command sent by the CMS for one single light point

**CTR-1****Manual control over a group of light points**

The Gateway properly receives and handles a manual override command sent by the CMS for a group of light points

**CTR-2****Manual control with a delay**

The Gateway properly receives and handles a manual override command that includes a delay, sent by the CMS for one single light point. **CTR-3**

**Manual control with a ramp**

The Gateway properly receives and handles a manual override command that includes a rampup, sent by the CMS for one single light point. **CTR-4**

**Automatic switch light on/off based on photocell value**

The Gateway can properly execute a control program that switches the light ON and OFF based on a local photocell value on a single light point. **CTR-5**

**Automatic change of light level when presence detected**

The Gateway can properly execute a control program that changes the light dimming level based on a local presence sensor on a single light point. **CTR-6**

**Automatic change of light level when noise detected**

The Gateway can properly execute a control program that changes the light dimming level based on a local noise sensor on a single light point. **CTR-7**

**Alarming**

4 of 5

**Report lighting alarms to the CMS** ✓

The Gateway can produce lighting alarms and send them to the CMS using one of the data logger services. **ALR-1**

**Report electrical alarms to the CMS** ✓

The Gateway can produce electrical alarms and send them to the CMS using one of the data logger services. **ALR-2**

**Report invalid program and calendar** ✓

The Gateway can produce invalid calendar and control program alarms and send them to the CMS using one of the data logger services. **ALR-3**

**Report activity for sensor based lighting**

The Gateway can send an event in case of activity detected and send them to the CMS using one of the data logger services. **ALR-4**

**Request the status of the alarm** ✓

The Gateway can report the status of the alarms as a response to a request from the CMS **ALR-5**

**Programming**

6 of 9

**Fix time switching+dimming control program that applies to all days in the year** ✓

The Gateway can receive and execute a control program that switches and dims a light point at fix time all days in the year. **PRG-1**

**Astro-clock switching + fix time dimming control program that applies to all days in the year**



The Gateway can receive and execute a control program that switches a light point at sunrise/sunset +/- few minutes and dim it during an astro-clock active period, all days in the year.

**PRG-2**

**Photocell switching + fix time dimming control program that applies to all days in the year**

The Gateway can receive and execute a control program that switches a light point when photocell indicates darkness and dim it during the photocell active period, all days in the year.

**PRG-3**

**Photocell and astro-clock switching + fix time dimming control program that applies to all days in the year**

The Gateway can receive and execute a control program that switches a light point when photocell indicates darkness or at sunrise/sunset +/- few minutes (the earlier for switch ON/OFF) and dim it during the photocell active period, all days in the year.

**PRG-4**

**Part night switching program**



The Gateway can receive and execute a control program that switches a light point OFF at fixed time in the middle of the night.

**PRG-5**

**Support exceptional periods (e.g., Sept 10th to Oct 16th)**



The Gateway can receive and execute a calendar that has a default rule for all days in the year and another higher priority calendar that applies from DAY 1 to DAY 2.

**PRG-6**

**Support exceptional week days (e.g., every Saturday and Sunday)**



The Gateway can receive and execute a calendar that has a default rule for all days in the year and another higher priority calendar that applies every Saturday night and Sunday night, every day in the year.

**PRG-7**

**Support exceptional week days (e.g., every Saturday and Sunday) and exceptional periods (e.g., Sept 10th to Oct 16th)**



The Gateway can receive and execute a calendar that has a default rule for all days in the year, another higher priority calendar that applies every Saturday night and Sunday night, every day in the year and another higher priority calendar that applies to every saturday between DAY 1 and DAY 2.

**PRG-8**

**Support dynamic lighting program based on sensor detection**

The Gateway can receive and execute a control program that has rule based on presence sensor.

**PRG-9**

## Capability list

### Security

Enabled

## Functions

### Basic

The Basic function describes the properties related to the physical asset to which the logical device is associated, such as identification (assetId) and location information.

#### Attributes

| # | Attribute       | Description  |
|---|-----------------|--|
| ✓ | serial          | Serial number of the device.   |
| ✓ | swVersion       | Software version installed on the device.  |
| ✓ | location        | Latitude, Longitude and Altitude. [DEPRECATED: This attribute has been deprecated and it will be removed in the next MAJOR release. Please use the new LocationSensorFunction.location instead.]   |
| ✓ | deviceReset     | The physical device containing the logical device was reset.   |
| ✓ | locationUpdated | Indicates the location of a device has changed, but detecting the change is outside the scope of the TALQ Specification. [DEPRECATED: This attribute has been deprecated and it will be removed in the next MAJOR release. Please use the new LocationSensorFunction.locationChanged instead.] |
| ✓ | currentTime     | Current time of the device defined as local time with time zone designator. [DEPRECATED: This attribute has been deprecated and it will be removed in the next MAJOR release. Please use the new TimeFunction.currentTime instead.]  |

#### Events

| # | Event type      | Description   |
|---|-----------------|---|
| ✓ | deviceReset     | The physical device containing the logical device was reset |
| ✓ | locationUpdated | Indicates the location of a device has changed.             |

### Communication

The Communication Function contains attributes related to the communication within the ODN, and between ODN devices and Gateways. Although communication within the ODN is outside the scope of the TALQ Smart City Protocol, this Function enables access to a minimum set of configuration and state information of the ODN communication interface in order to facilitate system management from the CMS.

#### Attributes

| # | Attribute            | Description  |
|---|----------------------|--|
| ✓ | physicalAddress      | Physical address of the device. For example, IEEE MAC address. This attribute can be used to map between logical and physical devices. The format is specific to the ODN implementation. |
| ✓ | communicationFailure | This attribute is updated by the ODN when the communication function is not operating as expected.   |

#### Events

| # | Event type           | Description   |
|---|----------------------|---|
| ✓ | communicationFailure | This event is generated by the ODN when the communication function is not operating as expected |

### Gateway

The Gateway function includes the necessary attributes to enable the communication between the CMS and the Gateway according to the TALQ Specification.

#### Attributes

| # | Attribute | Description |
|---|-----------|-------------|
|---|-----------|-------------|

|                  |   |
|------------------|---|
| ✓ cmsUri         | Base URI for TALQ communication that allows the Gateway to access the CMS. Must be an absolute URI. Other URI's for accessing CMS can be relative to this base.   |
| ✓ cmsAddress     | CMS UUID address  |
| ✓ gatewayUri     | Base URI for TALQ communication that allows the CMS to access the Gateway. Must be an absolute URI. Other URI's for accessing Gateway can be relative to this base.   |
| ✓ gatewayAddress | Gateway UUID address  |
| ✓ retryPeriod    | Time duration before the Gateway retransmits a message for which expected response has not been received. [DEPRECATED: This attribute has been deprecated and it will be removed in the next MAJOR release. Please use the new GatewayFunction.gatewayRetryPeriod instead.] |
| ✓ crlUrn         | URI where the Gateway can obtain the Certification Revocation List (CRL).   |
| ✓ vendor         | Vendor identification.  |

**Lamp Actuator**

The Lamp Actuator function includes attributes related to lighting control and it represents the smallest unit for control purposes. In practice, however, a Lamp Actuator function can control combinations of several lamps and control gear but all in the same way, as if they are all one individual unit.

**Attributes**

| # | Attribute            | Description   |
|---|----------------------|---|
| ✓ | defaultLightState    | Sets the default light output for the lamp actuator. This shall be applicable if no other command is active. This attribute shall be set to 100% as default value.  |
| ✓ | targetLightCommand   | Latest command for the lamp actuator.   |
| ✓ | feedbackLightCommand | This attribute reflects the command in effect and it might deviate from the actualLightState due to propagation time or due to internal ODN specific mechanisms to handle the priority of the requests.   |
| ✓ | actualLightState     | This attribute should reflect the physical state of the light source as much as possible, including factors such as CLO. It may be calculated or measured, depending on the specific ODN implementation, which is outside the scope of this specification.                |
| ✓ | calendarID           | TALQ Address of the calendar controlling this lamp actuator. If this attribute is empty, the behavior shall be determined by the ODN. If the attribute is invalid, the ODN shall trigger a generic invalid address event and the behavior shall be determined by the ODN. |
| ✓ | invalidProgram       | The lamp actuator function has been allocated a control program that it cannot implement.   |
| ✓ | lightStateChange     | Light state has changed.  |

**Events**

| # | Event type       | Description  |
|---|------------------|--|
| ✓ | lightStateChange | Light state has changed  |
| ✓ | invalidProgram   | The lamp actuator function has been allocated a control program that it cannot implement |

**Lamp Monitor**

The Lamp Monitor function enables monitoring of lamp parameters. A Lamp Monitor function should be associated with a specific lamp/control gear combination. Multiple lamp monitor functions may be implemented by a single device.

**Attributes**

| # | Attribute        | Description  |
|---|------------------|--|
| ✓ | activePower      | Active power.  |
| ✓ | activeEnergy     | Cumulative active energy (since installation or counter reset).      |
| ✓ | lampPowerTooHigh | Lamp power is greater than expected lamp power + lampPowerTolerance. |

|                          |  |
|--------------------------|--|
| ✓ lampFailure            | The lamp is not operating as it is supposed to (e.g. the lamp is broken). This event shall be used to detect a situation where the lamp (or LED module(s)) should be lit, but produce no light. This could be detected by the current flowing or power consumed. |
| ✓ relayFailure           | Set in case of internal relay is failing (e.g. it may be stuck in either on or off position). Typically if contactor error is used as well.  |
| ✓ controlGearCommFailure | Indicates failure of the control gear.   |
| ✓ supplyLoss             | Indicates loss of mains power.   |
| ✓ lampUnexpectedOn       | Indicates lamp is unexpectedly on.   |

**Events**

| # | Event type             | Description  |
|---|------------------------|--|
| ✓ | lampPowerTooHigh       | Lamp power is greater than expected lamp power + lampPowerTolerance  |
| ✓ | lampFailure            | The lamp is not operating as it is supposed to (e.g. the lamp is broken). This event shall be used to detect a situation where the lamp (or LED module(s)) should be lit, but produce no light. This could be detected by the current flowing or power consumed. |
| ✓ | relayFailure           | Set in case of internal relay is failing   |
| ✓ | controlGearCommFailure | Indicates failure of the control gear  |
| ✓ | supplyLoss             | Indicates loss of mains power  |
| ✓ | lampUnexpectedOn       | Indicates lamp is unexpectedly on  |

**Electrical Meter**

The electrical meter function supports electrical metering capabilities including measurements of voltage, current, power, energy, and power factor. This function may be associated with Luminaire Controllers, Cabinet Controllers or electrical meters installed in switch boxes. ODNs may implement both single phase and three phase meters. Typically meters within a control device will be single phase and stand-alone meters. A street side cabinet may have single phase or three phase meters.

**Attributes**

| # | Attribute         | Description  |
|---|-------------------|--|
| ✓ | totalActiveEnergy | Total cumulative kWh measured by the meter since installation date (or counter reset). |

**Events**

| # | Event type | Description |
|---|------------|-------------|
|---|------------|-------------|

**Services**

**Configuration Service**

The TALQ Configuration Service enables discovery and configuration of devices and services

**Options**

| # | Option                      | Value | Description   |
|---|-----------------------------|-------|---|
| ✓ | commissioningSupported*     |       | This ODN can support commissioning from the CMS side. |
| ✓ | devicesPaginationSupported* |       | This ODN can support pagination of devices.           |

**Control Service**

The Control service describes the mechanisms to operate the actuator functions in order to enable schedule based and override control

**Options**



| # | Option  | Value  | Description  |
|---|---|--|--|
| ✓ | supportedTypes                                    | <ul style="list-style-type: none"> <li>AbsoluteActivePeriod</li> <li>AstroClockActivePeriod</li> <li>ccDay*</li> </ul> | Control Program and calendar options supported are defined by announcing support for the given modes |
| ✓ | dayOffset   | • 0  | Offset of start of day   |
| ✓ | programSecondsSupported*                          |  | Indicates whether the field of seconds is supported in programs.                                     |
| ✓ | maxNumberOfPowerFactorThresholdDimmingCurveItems* |  | Maximum number of items at the powerFactorThresholdDimmingCurve of the LampType.                     |

**Events**

| # | Event Type      | Description  |
|---|-----------------|--|
| ✓ | invalidCalendar | An invalid calendar has been provided by the CMS to the ODN                            |
| ✓ | invalidProgram  | A control program has been provided by the CMS, which cannot be implemented by the ODN |

**Data Collection Service**

The TALQ Data Collection Service is a provision to configure how ODN measurements, status information and events are logged, and when or under what conditions the logged data is transferred to the CMS

**Options**

| # | Option         | Value   | Description                             |
|---|----------------|---|---|
| ✓ | supportedModes | <ul style="list-style-type: none"> <li>VendorRecordingMode</li> <li>EventRecordingMode</li> <li>ImmediateReportingMode</li> </ul> | Recording and Reporting modes supported |

**Events**

| # | Event Type          | Description  |
|---|---------------------|--|
| ✓ | invalidLoggerConfig | The CMS has provided a data logger configuration that cannot be implemented by the ODN |

**On Demand Data Request Service**

This service provides the mechanism to access attributes in the logical devices by requesting attribute values from the ODN

**Group Management Service**

This service provides the mechanisms to define and manage groups

**Options**

| # | Option                | Value | Description                               |
|---|-----------------------|-------|---|
| ✓ | maximumNumberOfGroups |       | Maximum number of groups per Gateway      |
| ✓ | maximumGroupSize      |       | Maximum number of group members per group |

**Test Service**

This service provides a mechanism to reduce the human intervention during the certification tests, enabling the certification tests to maximise automation

## Objects

### Event log data

Event log data contains a single event, with eventType and value, in each single log entry. It also includes information about whether the log denotes the start or end of the event. Furthermore additional information can be added with the info attribute.

#### Properties

| # | Property   | Description   |
|---|------------|---|
| ✓ | eventType  | Identifier of event reported  |
| ✓ | srcAddress | Address of Logical device or function within a logical device which is the source of the event or to which this event applies |

### Command

A command defines a type of control action that can be applied to a function. Commands can be generated by a manual override action or by a control program.

#### Properties

| # | Property | Description   |
|---|----------|---|
| ✓ | state    | Light state to be applied to the lamp actuator  |
| ✓ | cmsRefId | CMS reference, which can be used for data logging. The cmsRefId in a Command is a free text to be used by the CMS for any purpose, e.g: to differentiate contexts. It is a token that allows the CMS to match client requests to the original notification. |

### Group


A group is set of entities that can be addressed by the same group address. Devices and functions within devices can be assigned to a group. A group may also include other groups as members.

#### Properties

| # | Property | Description                            |
|---|----------|--|
| ✓ | address  | Group address                          |
| ✓ | members  | TALQ Addresses of members of the group |
| ✓ | purpose  | Main purpose of the group              |

\*: The Certification Test Tool is designed to provide a high level of confidence that complementary systems can communicate successfully. As both the protocol and the test tool evolve, all mandatory and other core tests are confirmed by comparison with real-life scenarios (plug-fest or similar). Some tests of optional and more peripheral features may not yet have been confirmed in this way; such features are identified with an asterisk (\*).

This Capability List is based on a certification session performed by the TALQ Certification Tool (v2.6.1-online.7) on 2024-10-27 11:34:04.889 +0100.

 and **TALQ** are trademarks owned by the TALQ Consortium.

 TALQ Consortium

